



1.8 GHz to 2.0 GHz

Model No.	Frequency 1 GHz	Frequency 2 GHz	Gain dB (Min/Typ)	Flatness dB (Max/Typ)	Noise dB (Max/Typ)	P-1dB dBm (Min/Typ)	IP3 dBm (Typ)	VSWR Input (Max/Typ)	VSWR Output (Max/Typ)	+12 /+15 VDC Current (mA) Nom/Max	Size
CA12-2075	1.8	2.0	24	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2076	1.8	2.0	24	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2077	1.8	2.0	24	±0.5	0.8	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2078	1.8	2.0	24	±0.5	0.7	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2081	1.8	2.0	24	±0.5	1.2	13	23	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2082	1.8	2.0	24	±0.5	1.2	15	25	2.0:1/1.5:1	2.0:1/1.5:1	100	LCFB1
CA12-2083	1.8	2.0	23	±0.5	1.2	17	27	2.0:1/1.5:1	2.0:1/1.5:1	120	LCFB1
CA12-2084	1.8	2.0	23	±0.5	1.4	20	30	2.0:1/1.5:1	2.0:1/1.5:1	150	LCFB1
CA12-2085	1.8	2.0	23	±0.5	1.5	23	33	2.0:1/1.5:1	2.0:1/1.5:1	200	LCFB1
CA12-2086	1.8	2.0	22	±0.5	1.8	27	35	2.0:1/1.5:1	2.0:1/1.5:1	450	LCFB1
CA12-2087	1.8	2.0	22	±0.5	2.0	30	38	2.0:1/1.5:1	2.0:1/1.5:1	650	LCFB1
CA12-3075	1.8	2.0	32	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3076	1.8	2.0	32	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3077	1.8	2.0	32	±0.5	0.8	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3078	1.8	2.0	32	±0.5	0.7	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3081	1.8	2.0	32	±0.5	1.2	13	23	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3082	1.8	2.0	32	±0.5	1.2	15	25	2.0:1/1.5:1	2.0:1/1.5:1	140	FB2
CA12-3083	1.8	2.0	32	±0.5	1.2	17	27	2.0:1/1.5:1	2.0:1/1.5:1	170	FB2
CA12-3084	1.8	2.0	31	±0.5	1.4	20	30	2.0:1/1.5:1	2.0:1/1.5:1	200	FB2
CA12-3085	1.8	2.0	31	±0.5	1.5	23	33	2.0:1/1.5:1	2.0:1/1.5:1	250	FB2
CA12-3086	1.8	2.0	30	±0.5	1.8	27	35	2.0:1/1.5:1	2.0:1/1.5:1	500	FB2
CA12-3087	1.8	2.0	30	±0.5	2.0	30	38	2.0:1/1.5:1	2.0:1/1.5:1	750	FB2

Ciao Wireless, Inc.

4000 Via Pescador / Camarillo / CA 93012

Tel (805) 389-3224 / Fax (805) 389-3629 / ciaowireless.com