

Model Number	Frequency Range GHz	Number of Ports (N-Way)	Insertion Loss dB(max)	VSWR In/Out (max)	RMS Amplitude Variation dB (max)	RMS Phase Variation Degrees (max)
Radial Power Combiners/Dividers:		400 to 500 MHz				
CWC004005-3201	0.4-0.5	32	0.25	1.4:1	0.25	2.0
CWC004005-3601	0.4-0.5	36	0.25	1.4:1	0.30	2.0
CWC004005-4801	0.4-0.5	48	0.35	1.4:1	0.35	4.0
Radial Power Combiners/Dividers:		1.2 to 1.4 GHz				
CWC012014-1601	1.2-1.4	16	0.25	1.4:1	0.25	2.0
CWC012014-3201	1.2-1.4	32	0.30	1.4:1	0.30	2.0
CWC012014-4801	1.2-1.4	48	0.35	1.4:1	0.35	4.0
Radial Power Combiners/Dividers:		1.85 to 1.95 GHz				
CWC018019-1601	1.85-1.95	16	0.25	1.4:1	0.25	2.0
CWC018019-3201	1.85-1.95	32	0.30	1.4:1	0.30	2.0
CWC018019-4801	1.85-1.95	48	0.35	1.4:1	0.35	4.0
Radial Power Combiners/Dividers:		2.7 to 2.9 GHz				
CWC027029-1601	2.7-2.9	16	0.30	1.4:1	0.25	1.5
CWC027029-2401	2.7-2.9	24	0.30	1.4:1	0.25	2.0
CWC027029-2801	2.7-2.9	28	0.50	1.4:1	0.30	2.0
CWC027029-3201	2.7-2.9	32	0.50	1.4:1	0.30	2.0
CWC027029-3601	2.7-2.9	36	0.60	1.4:1	0.40	4.0
CWC027029-4801	2.7-2.9	48	0.60	1.4:1	0.40	4.0
CWC027029-5001	2.7-2.9	50	0.70	1.4:1	0.50	5.0
CWC027029-6401	2.7-2.9	64	0.70	1.4:1	0.50	5.0
CWC027029-6801	2.7-2.9	68	0.70	1.4:1	0.50	5.0
Radial Power Combiners/Dividers:		2.9 to 3.5 GHz				
CWC029035-2401	2.9-3.5	24	0.30	1.4:1	0.25	2.0
CWC029035-3601	2.9-3.5	36	0.50	1.4:1	0.30	2.0
CWC029035-4801	2.9-3.5	48	0.60	1.4:1	0.40	4.0
Radial Power Combiners/Dividers:		5.4 to 5.9 GHz				
CWC054059-1601	5.4-5.9	16	0.30	1.4:1	0.25	2.0
CWC054059-2401	5.4-5.9	24	0.30	1.4:1	0.25	2.0
CWC054059-3201	5.4-5.9	32	0.50	1.4:1	0.30	2.0
CWC054059-4801	5.4-5.9	48	0.60	1.4:1	0.40	4.0
Radial Power Combiners/Dividers:		5.9 to 6.4 GHz				
CWC054064-1601	5.9-6.4	16	0.30	1.4:1	0.25	2.0
CWC059064-2401	5.9-6.4	24	0.30	1.4:1	0.25	2.0
CWC059064-3601	5.9-6.4	36	0.50	1.4:1	0.30	2.0
CWC059064-4801	5.9-6.4	48	0.60	1.4:1	0.40	4.0
Radial Power Combiners/Dividers:		10.0 to 10.7 GHz				
CWC100107-1601	10.0-10.7	16	0.30	1.4:1	0.25	1.5
CWC100107-2401	10.0-10.7	24	0.30	1.4:1	0.25	2.0
CWC100107-3201	10.0-10.7	32	0.50	1.4:1	0.30	2.0
CWC100107-3601	10.0-10.7	36	0.50	1.4:1	0.30	2.0
CWC100107-4801	10.0-10.7	48	0.60	1.4:1	0.40	4.0
CWC100107-5001	10.0-10.7	50	0.60	1.4:1	0.40	4.0
CWC100107-6401	10.0-10.7	64	0.70	1.4:1	0.50	5.0
CWC100107-6801	10.0-10.7	68	0.70	1.4:1	0.50	5.0

Please visit Ciao Wireless' website at www.ciaowireless.com for a greater listing of models and additional frequencies.